

AVPro Edge Crestron Home Driver

Notice

Please be aware that this is a beta release of the AVPro Edge Crestron Home switcher driver, if you have any issues please check for a newer version or report the issue to the driver provider.

Please ensure that your crestron home processor is running version 3.003.0035.

There is currently an issue with 3rd Party switcher drivers running in firmware versions greater than 3.003.0035.

There is an known issue when using the crestron home iPad app, volume return to zero after it has been changed. Please test this driver with the crestron setup app

Introduction

This driver suite enables control of the AVPro Edge switcher products via Crestron Home. The zip file comprises of drivers (pkg files). Crestron home currently supports matrix switchers up to 15x15, therefore input and outputs greater than number will not be displayed in crestron home setup.

Driver installation

To install these driver on a Crestron Home system they need to be 'Side loaded' into the processor. Please follow the steps below:

1. In Crestron Toolbox open File Manager and connect to your Crestron Home Processor.
2. Browse to the user/ThirdPartyDrivers/Import directory.
3. Drag the pkg files from the zip file into the Import directory.
4. In the Crestron home setup app go to settings and configure system.
5. In the setup area select Pair Device.

6. Select Third Party. **Please be aware you need to press the Third Party button for the drivers to refresh. If you are in a higher level press back until you can select 'Third Party'**
7. Find the control driver in the AV Switcher menu under AVPro Edge.
8. Add the drivers and configure as normal.

Updating Drivers

Please follow the process below to update your drivers.

1. Make a note of the configuration of your AVR drivers in the Crestron Home App.
2. Remove **all** instances of the AVPro Edge driver from the Crestron Home App.
3. Reboot the processor via the System settings button (Cog), System Configuration and then Reboot.
4. After the processor has rebooted follow the Driver installation process above.